

Product datasheet

Specifications

Plug, Easy56, 3 Pin, 10A, 250V



EY56P310

Main

Product name	Easy56
Product or component type	Plug
Device short name	EY56P310
Plug, socket category	Low voltage
Poles description	1P + N + E
Pin number	3 pins
Shape of pin	Flat
Outlet standard deviation	Australian/New Zealand

Complementary

Plug, socket, control station shape	Straight
[In] rated current	10 A
[Ue] rated operational voltage	250 V
Network type	AC
Network frequency	50 Hz
Material	Polycarbonate: housing
Contacts material	Pins: brass
Connections - terminals	Screw terminals
Cable cross section	0.75...1 mm²
Cable outer diameter	6.8...10.6 mm
Wire stripping length	12...34 mm
cabl e entry	Cable gland
Thread type	M20
Net weight	0.107 kg
Height	67 mm
Width	67 mm
Depth	112.5 mm
Colour	Plug: orange (RAL 2004) Body: clear

Environment

Standards	AS/NZS 3112
-----------	-------------

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Quality labels	RCM
IP degree of protection	IP66 conforming to AS 60529
Ambient air temperature for operation	-25...75 °C
Ambient air temperature for storage	-25...75 °C

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	7 cm
Package 1 Width	7 cm
Package 1 Length	12.5 cm
Package 1 Weight	114 g

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

 Environmental footprint	
Total lifecycle Carbon footprint	1

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration

Use Again

 Repack and remanufacture	
Take-back	No