

Product datasheet

Specifications



Push Button Switch LED, Saturn Series, 1 Gang, 20A

4061PBL-OM

 **Discontinued on:** 10 Sept 2025

 **To be discontinued**

Main

Range of product	Saturn Series 4000
Product or component type	Push-button
Colour	Ocean mist
Product brand	Clipsal
Device presentation	Basic element with full cover plate

Complementary

Colour code	OM
Actuator	Push-button
Number of gangs	1 gang
Local signalling	Indicator light
fixing mode	By screws
Material	PVC (polyvinyl chloride)
Surface finish	Glossy
[Ue] rated operational voltage	250 V AC
Inrush current	20 A
Height	116 mm
Depth	43.6 mm
Embedding depth	31.6 mm
Width	75 mm
Mounting position	Vertical

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5 cm
Package 1 Width	12.9 cm
Package 1 Length	9.1 cm
Package 1 Weight	140 g

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

 Environmental footprint	
Total lifecycle Carbon footprint	5
Environmental Disclosure	Product Environmental Profile

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration

Use Again

 Repack and remanufacture	
End of life manual availability	No need of specific recycling operations
Take-back	No